

DigiSender® ZX7

QUAD INPUT 5.8GHz WIRELESS AV SENDER Model: DG458







Introduction to DigiSenders 5.8GHz Analogue



The DigiSender® ZX7 will allow you to send the Audio, Video and Remote Control Signals from up to 4 sources to another television in your home and because it uses the very latest in 5.8GHz transmission technology, you can rest assured that it will be free from interference.

The IR Systeme Technik™ Remote Relay Kit provides an easy means of using your source remote controls from the receiving location and the incorporated DigiEye™ technology provides unsurpassed compatibility with all makes of set top box.

DG458

Features

- 5.8GHz Operating Frequency
- No interference from 2.4GHz Devices like Wi-Fi & Bluetooth
- Sleek Piano Black Design
- DigiConnector™ SCART Inputs
- Phono Outputs on the Receiver for connecting to a Hi-Fi
- Stunning DVD Quality Video
- Crystal Clear Hi-Fi Stereo Sound
- DigiEye™ Remote Relay Technology (IrDA, RC5/6)
- IR Systeme Technik™ Remote Relay Kit
- Widescreen Compatible
- Works Through Walls & Ceilings
- Fitted In Minutes
- Additional Receivers available

Packaging & Shipping Information

- Retail Packaging Dimensions: L: 260mm, W: 330mm, H: 60mm
- Retail Packaging Weight: 1.4kg
- Shipping Carton Dimensions: L: 645mm, W: 275mm, H: 350mm
- Shipping Carton Weight: 15kg
- Units per Carton: 10

Specifications

- Transmitter Inputs: 2x DigiConnector™ SCART, 2x Phono (Audio L&R, Video)
- Receiver Outputs: 1x SCART, 1x Phono (Audio L&R, Video)
- Audio/Video Frequency: 5.725GHz ~ 5.875GHz
- Audio/Video Channels: 4
- Remote Relay Frequency: 433MHz
- Remote Relay Channels: 16
- Remote Control Compatibility: IrDA, RC5, RC6
- Video Input Level: 1V Peak-Peak 75Ω
- Video Input Colour: PAL
- Audio Input Level: 1V PP Mod 1KHz, Dev 15KHz
- Audio Bandwidth: 20Hz-22KHz (-3dB)
- Sensitivity: -90dB
- Antenna: External
- Range: 100m (Clear Line of Sight)
- Power Supplies: 9VDC 300mA
- Dimensions: L: 100mm, W: 160mm, H: 40mm
- Weight: 0.3kg



